



Model:DM102



Model:DM102S



Model:DM102SL

Digital Rotary Dimmer Switch Series



FEATURES

- Compatible with up to 150W dimmable LED /CFL bulbs as well as 600W Incandescent bulbs.
- Convenient operation, push on and off switch with full-range rotary dimming control, fade-in start up and fluid movement.
- Easy installation, no removal of fins required for multi-gang installations.
- Classic and precise design, good match for creating room's ambiance .
- Slim and compact size for easy installation in a standard junction box.
- Compared with standard switch, rotary dimmer switch provides smooth and precise diming performance as per your request so as to save energy.
- Low end adjust, allow users to preset minimum light level to avoid flickering at lower diming levels and realize maximal diming range.
 - * (only for DM102S and DM102SL)
- The dimmer features a location indicator LED light making it easy for you to find in the dark
 - * (only for DM102SL)

SPECIFICATIONS

Item	DM102	DM102S	DM102SL
Rating Input	AC 120V 60Hz		
Rating Wattage	Incandescent 600W, LED/CFL 150W(1.5A)		
Wiring configurations	Single Pole / 3-Way		
Switch type	Push switch		
Dimming type	Rotary dimming		
Low-end trim	×	√	√
LED indicating lamp	×	×	√
Fade on	√	√	√
Cover and Body Material	Thermoplastic		
Flammability	V-2 per UL94		
Operating Temperature	-10°C to 40°C		
Storage Temperature	-40°C to 85°C		
Termination	Back & Side		
Terminal Accom.	18-12 AWG		
Standards	UL 1472		
Certifications	UL/CUL listed		
FCC Part15B	√	√	√

